



**Eur päisches
Patentamt**

**European
Patent Office**

**Office européen
des brevets**

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr.

Patent application No.

Demande de brevet n°

03004669.2

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

R C van Dijk

THIS PAGE BLANK (USPTO)



Anmeldung Nr:
Application no.: 03004669.2
Demande no:

Anmeldetag:
Date of filing: 03.03.03
Date de dépôt:

Anmelder/Applicant(s)/Demandeur(s):

Rohde & Schwarz GmbH & Co. KG
Mühlendorfstrasse 15
D-81671 München
ALLEMAGNE

Bezeichnung der Erfindung/Title of the invention/Titre de l'invention:
(Falls die Bezeichnung der Erfindung nicht angegeben ist, siehe Beschreibung.
If no title is shown please refer to the description.
Si aucun titre n'est indiqué se référer à la description.)

Method and analysing device for analysing an OFDM signal

In Anspruch genommene Priorität(en) / Priority(ies) claimed /Priorité(s)
revendiquée(s)

Staat/Tag/Aktenzeichen/State/Date/File no./Pays/Date/Numéro de dépôt:

EP/09.12.02/EP 02027409

Internationale Patentklassifikation/International Patent Classification/
Classification internationale des brevets:

H04L27/26

Am Anmeldetag benannte Vertragstaaten/Contracting states designated at date of
filing/Etats contractants désignées lors du dépôt:

AT BE BG CH CY CZ DE DK EE ES FI FR GB GR HU IE IT LU MC NL
PT SE SI SK TR LI

72

→ BLANK (USPTO)

P27512/EP/P1

Method and Analysing Device for analysing an OFDM signal

5 This application concerns a simplified analysis of an OFDM
(Orthogonal Frequency Division Multiplex)-signal,
especially an OFDM signal for Wireless LAN as defined in
IEEE802.11a, Part 11: "Wireless LAN Medium Access Control
(MAC) and Physical Layer (PHY) specifications" referred
10 herein as IEEE W-LAN Standard.

It is the principle of an OFDM system to transmit the
signal via several orthogonal sub-carriers. The principle
of OFDM is explained e.g. in Hermann Rohling, Thomas May,
15 Karsten Brüninghaus und Rainer Grünheid, "Broad-Band OFDM
Radio Transmission for Multimedia Applications",
Proceedings of the IEEE, Vol. 87, No. 10, October 1999,
pages 1778 ff.

20 A receiver design for wireless broad-band systems is known
from Speth, Fechtel, Fock, Meyr: "Optimum Receiver Design
for Wireless Broad-Band Systems Using OFDM - Part I", IEEE
Trans. On Comm. Vol. 47, No. 11, Nov. 1999, pages 1668 -
1677 and Speth, Fechtel, Fock, Meyr: "Optimum Receiver
25 Design for Wireless Broad-Band Systems Using OFDM - Part
II", IEEE Trans. On Comm. Vol. 49, No. 4, April 2001,
pages 571 - 578.

The signal of wireless LAN systems is analysed in order to
30 monitor the signal quality. For example the error vector
magnitude *EVM* of the whole signal or of specific sub-
carriers is a typical parameter to describe the signal
quality.

35 In the past only analysing devices with wideband signal
processing, especially with a wideband intermediate
frequency *IF* section, have been used. Such analysing
devices with wideband signal processing are, however,
rather expensive.

Thus, it is the object of the present invention to provide a method and an analysing device being able to analyse wideband OFDM signals, especially wireless LAN signals, in spite of their reduced bandwidth.

The object is solved by the features of claim 1 or claim 4 concerning the method and by the features of claim 12 or claim 13 concerning the analysing device. Claim 14 concerns a storage medium storing a respective computer program and claims 15, 16 and 17 concern a respective computer-program-product and computer program.

According to the invention the spectrum of the OFDM signal can be shifted so that different parts of the OFDM spectrum can lie within the reduced bandwidth of the analysing device. Low pass filtering is necessary to suppress the mirror frequency and to limit the input bandwidth for a resampler following in the signal path.

According to one aspect of the invention the length of the impulse response of the low pass filter is shorter than the length of the guard periods of the data symbols.

The OFDM signal, especially the OFDM signal for wireless LAN application, generally has several pilot channels at specific carrier frequencies. According to IEEE W-LAN standard there are four carrier frequencies transporting a pilot signal. As the analysing device has a reduced bandwidth, not all pilot channels lie within the reduced bandwidth of the analysing device. For example, the number of useable pilot channels can be reduced from four to two. The analysing device has to estimate several synchronisation parameters of the OFDM signal, e.g. frequency offset, time or clock offset, phase offset resulting from the frequency offset and the clock offset and the gain. The accuracy of the estimation of these parameters is reduced due to the fact that only a reduced number of pilot channels can be used for the estimation.

According to another aspect of the present invention this is compensated by averaging the estimated synchronisation parameters in OFDM-symbol direction in order to achieve the same accuracy which would apply to the use of the original number of pilot channels.

The dependent claims concern further developments of the invention.

10 An embodiment of the present invention is described in the following with reference to the drawings. In the drawings

Fig. 1 shows the block diagram of a conventional analysing device;

15

Fig. 2 shows the block diagram of an inventive analysing device;

Fig. 3 shows the spectrum of the OFDM signal and the reduced bandwidth of signal section 20 of the inventive analysing device;

20

Fig. 4 shows a symbol sequence of one channel of the OFDM signal with the useful part and the guard period;

25

Fig. 5 shows a schematic diagram of impulse response of low pass filter 24 and

Fig. 6 shows an example of the screen of the analysing device with specific diagrams.

30

This following description with reference to fig. 1 gives a rough view over the signal processing of the IEEE802.11a application. Details are disregarded in order to get a concept overview.

35

In the following text the abbreviations

	$a_{l,k}$	symbol l of sub-carrier k
	EVM_k	error vector magnitude of sub-carrier k
	EVM	error vector magnitude of current packet
5	Δf	frequency deviation between transmitter Tx and receiver Rx
	l	symbol index $l = [1, \text{nof_Symbols}]$
	nof_symbols	number of symbols of payload
10	H_k	channel transfer function of sub-carrier k
	k	channel index $k = [-31, 32]$
	K_{mod}	modulation dependant normalisation factor
15	ξ	relative clock error of reference oscillator
	$r_{l,k}$	sub-carrier k of symbol l

are used. In this application the hat $\hat{\cdot}$ generally describes an estimate. Example: \hat{x} is the estimate of x . In this application the tilde $\tilde{\cdot}$ generally describes a trial parameter. Example: \tilde{x} is the trial parameter of x .

The diagram of the interesting blocks of analysing device 40 is shown in fig. 1. First the RF signal is downconverted to the intermediate IF frequency, e.g. $f_{IF} = 20.4$ MHz. The resulting IF signal $r_{IF}(t)$ is shown on the left-hand side of fig. 1. After band pass filtering in block 1 of IF signal section 20, the signal is sampled by an analog to digital converter (ADC) 2 at a sampling rate of e.g. $f_{s1} = 81.6$ MHz. This digital sequence is resampled in resampler 3 to the new sampling frequency of e.g. $f_{s2} = 80$ MHz which is a multiple of the Nyquist rate (20 MHz). The subsequent digital down converter 4 shifts the IF signal to the complex base band. In the next step the base band signal is filtered by a FIR filter 5. To get an idea, the rough transfer function is plotted in fig. 1. This FIR filter 5 fulfils two tasks: first it suppresses the IF

image frequency, secondly it attenuates the aliasing frequency bands caused by the subsequent down sampling in down sampler 6. After filtering, the sequence is sampled down by the factor of 4. Thus, the sampling rate of the down sampled sequence $r(i)$ is the Nyquist rate of $f_s = 20$ MHz. Up to this point the digital part of IF signal section 20 can be implemented in an ASIC.

In the lower part of fig. 1 the subsequent digital signal processing is shown and designated as W-LAN application block 7. In the first block 8 the packet search is performed. This block 8 detects the long symbol LS and recovers the timing. The coarse timing is detected first. This search is preferably implemented in the time domain. The algorithm is based on the cyclic repetition within the LS after $N = 64$ samples. Furthermore, a coarse estimate Δf_{coarse} of the receiver-transmitter Rx-Tx frequency offset Δf is derived from the metric. This can easily be understood because the phase of $r(i) \cdot r^*(i+N)$ is determined by the frequency offset. As the frequency deviation Δf can exceed half a bin (distance between neighbour sub-carriers) the preceding short symbol SS is also analysed in order to detect the ambiguity.

After the coarse timing calculation the time estimate is improved by the fine timing calculation. This is achieved by first estimating the coarse frequency response $\hat{H}_k^{(coarse)}$, with $k = [-26, 26]$ denoting the channel index of the occupied sub-carriers. First, the fast fourier transform FFT of the long symbol LS is calculated. After the FFT calculation the known symbol information of the LS sub-carriers is removed dividing by the symbols. The result is a coarse estimate $\hat{H}_k^{(coarse)}$ of the channel transfer function. In the next step the complex channel impulse response is computed by an IFFT. Next, the energy of the windowed impulse response (the window size is equal to the guard period) is calculated for every trial time. Afterwards, the trial

time of the maximum energy is detected. The trial time is used to adjust the timing.

Now the position of the long symbol LS is known and the starting point of the useful part of the first payload symbol can be derived. In the next block 9 this calculated time instant is used to position the payload window. Only the payload part is windowed. This is sufficient because the payload is the only subject of the subsequent measurements.

In the next block 10 the windowed sequence is compensated by the coarse frequency estimate $\Delta\hat{f}_{coarse}$. This is necessary because otherwise inter channel interference (ICI) would occur in the frequency domain.

The transition to the frequency domain is achieved by an fast fourier transform FFT of e.g. length 64 in block 11. The FFT is performed symbolwise for everyone of the $nof_symbols$ symbols of the payload. The calculated FFTs are described by $r_{l,k}$ with the symbol index $l=[1,nof_symbols]$ and the channel index $k=[-31,32]$ for example.

In case of an additive white Gaussian noise (AWGN) channel the FFT can be described by

$$r_{l,k} = K_{mod} \cdot a_{l,k} \cdot H_k \cdot e^{j2\pi N_s / N \phi_k l} + n_{l,k} \quad (1)$$

with

the modulation-dependant normalisation factor K_{mod} ,

the symbol $a_{l,k}$ of sub-carrier k at symbol l ,

the channel frequency response H_k ,

the phase drift ϕ_k of sub-carrier k within one useful part of the symbol T (see below),

the number of Nyquist samples, e.g. $N_s = 80$ of the symbol period,

the number of Nyquist samples, e.g. $N = 64$ of the useful part of the symbol and

5 the independent Gaussian distributed noise samples $n_{l,k}$.

Furthermore, the channel dependant phase drift ϕ_k (phase drift within one useful part of the symbol) is given by

10

$$\phi_k = \xi \cdot k + \Delta f T \quad (2)$$

whereas

15 ξ = the relative clock deviation of the reference oscillator and

Δf = the (not yet compensated) frequency deviation.

In eq. (1) both the phase drift ϕ_k caused by the not yet compensated frequency deviation Δf and the clock deviation ξ may not be neglected. This is illustrated by an example: In accordance with the IEEE W-LAN Standard the allowed clock deviation of the device under test (DUT) is up to $\xi_{\max} = 20$ ppm. Furthermore, a long packet with
 20 $nof_symbols = 400$ symbols is assumed. From eq. (1), (2) it results that the phase drift of the highest sub-carrier $k=26$ in the last symbol $l=no_symbols$ is 93 degrees. Even in the noise free case this would lead to symbol errors. The example shows that it is also necessary to estimate
 25 and compensate the clock deviation, which is accomplished in the estimation block 12 using pilot table 13 and in the compensation blocks 14 and 15.
 30

As discussed above, the FFT must be followed by the joint
 35 estimation of the gain g , the fine frequency deviation Δf and the clock deviation ξ . Concerning to IEEE W-LAN

Standard, Chapter 17.3.9.7, "Transmit modulation accuracy test", the phase drift must be estimated from the pilot sub-carriers. Hence the estimation is performed independently for every symbol, the symbol index l is
 5 appended to the estimation parameters in the subsequent formulas.

In addition the tracking of the gain g is supported symbol for symbol. The reason is that the reference gain
 10 $g=1$ occurs at the time instant of the long symbol. At this time the coarse channel transfer function $\hat{H}_k^{(coarse)}$ is calculated. This is useful because before symbol estimation the sequence $r'_{l,k}$ is compensated by the coarse channel transfer function $\hat{H}_k^{(coarse)}$. Consequently a potential
 15 change of the gain at the symbol l (caused, for example, by the increase of DUT amplifier temperature) would increase the symbol error rate especially at large symbol alphabet M of the MQAM transmission. In this case the estimation and the subsequent compensation of the gain is
 20 useful. In the subsequent formulas the gain at the symbol l will be described by the parameter g_l .

In this application the optimum maximum likelihood algorithm is used. Consequently, the log likelihood
 25 function

$$L(\tilde{g}_l, \Delta\tilde{f}_l, \tilde{\xi}_l) \stackrel{eq.(1)}{=} \sum_{k=-21, -7, 7, 21} \sum_{l=1}^{nof_symbols} |r_{l,k} - a_{l,k} \cdot \tilde{g}_l \cdot \hat{H}_k^{(coarse)} \cdot e^{j2\pi N_s / N \cdot \tilde{\phi}_k \cdot l}|^2 \quad (3)$$

with $\tilde{\phi}_k \stackrel{eq.(2)}{=} \tilde{\xi}_l \cdot k + \Delta\tilde{f}_l T$

30 is calculated as a function of the trial parameters $\tilde{g}_l, \Delta\tilde{f}_l$ and $\tilde{\xi}_l$. Finally, the trial parameters leading to the minimum of the log likelihood function are used as estimates $\hat{g}_l, \hat{\Delta f}_l$ and $\hat{\xi}_l$. In eq. (3) the known pilot symbols $a_{l,k}$ are read from table 13. It can be shown that the
 35 search procedure is independent of the frequency response

H_k (see eq. (3)). Therefore, only the current $r_{l,k}$ and $a_{l,k}$ are required. This robust algorithm even works well at low signal to noise ratios of about 5 dB with the Cramer Rao Bound being reached.

5

After estimation the three parameters, the sequence $r_{l,k}$ is compensated in the compensation blocks 14 and 15. In the upper analysing branch the compensation is user-defined i.e. the user determines which of the three parameters are compensated in compensation block 14. This is useful in order to extract the influence of these parameters. The resulting output sequence is described by $r'_{l,k}$. In the lower compensation branch the full compensation is always performed in compensation block 15. This separate compensation is necessary in order to avoid symbol errors. After the full compensation the secure estimation of the data symbols $\hat{a}_{l,k}$ is performed. From equation (1) it is clear that first the channel transfer function H_k must be removed. This is achieved by dividing the known coarse channel estimate $\hat{H}_k^{(coarse)}$ calculated from the LS. Usually an error free estimation of the data symbols can be assumed.

Concerning IEEE W-LAN Standard, Chapter 17.3.9.7, "Transmit modulation accuracy test", a better channel estimate \hat{H}_k of the data and pilot sub-carriers must be calculated by using the whole *nof_symbols* symbols of the payload. This can be accomplished in block 18 at this point because the phase is compensated and the data symbols are known.

30

In the following block 16 $r'_{l,k}$ is divided by the improved estimates \hat{H}_k . The resulting channel compensated sequence is described by $r''_{l,k}$.

35 In the last block 19 the measurement variables are calculated. The most important variable is the error vector magnitude

$$EVM_k = \sqrt{\frac{1}{nof_Symbols} \cdot \sum_{l=1}^{nof_Symbols} |r'_{l,k} - K_{mod} \cdot a_{l,k}|^2} \quad (4)$$

of the sub-carrier k of the current packet. Furthermore,
 5 the packet error vector magnitude

$$EVM = \sqrt{\frac{1}{52} \cdot \sum_{\substack{k=-26 \\ (k \neq 0)}}^{26} EVM_k^2} \quad (5)$$

is derived by averaging the squared EVM_k versus k .
 10 Finally, the average error vector magnitude

$$\overline{EVM} = \sqrt{\frac{1}{nof_packets} \sum_{counter=1}^{nof_packets} EVM^2(counter)} \quad (6)$$

is calculated by averaging the packet EVM of all
 15 $nof_packets$ detected packets. This parameter is equivalent
 to the so-called "RMS average of all errors $Error_{RMS}$ " of the
 IEEE802.11a measurement commandment, see IEEE W-LAN
 Standard, Chapter 17.3.9.7.

20 In the following text the abbreviations

	f_{IF}	IF frequency
	f_{bin}	frequency distance between neighbour sub-carriers
25	$H_{_\}(f)$	filter transfer function
	i	time index of the sampled sequence
	k	channel index of occupied sub-carriers $k = [-26, 26]$
	$T_s = 1/f_s$	sample period and frequency respectively
30		

are used.

Fig. 1 describes the W-LAN signal processing using a wide-band signal section 20, such as Rohde & Schwarz device FSQ. The available bandwidth of the FSQ is 27 MHz and therefore sufficient to measure the IEEE802.11a signal with a bandwidth of 16.4 MHz.

In the following the W-LAN application is discussed using an signal section 20 of the analysing device 40 with narrower bandwidth, such as Rohde & Schwarz device FSP. The problem is the smaller FSP analyser bandwidth of 8 MHz which only covers half of the OFDM signal bandwidth. The main idea of the present invention is to analyse the spectrally cut measurement signal with carefully designed filters. Simulations have shown that following properties can be expected:

- About 20 of the 52 sub-carriers can be analysed within a measurement.
- The position of the analysing window can be selected by the operator, e.g. to analyse the left, the middle or the right sub-carriers.
- Also symbolwise tracking of timing, phase and gain is supported.

25

In fig. 2 the diagram of the interesting blocks of signal section 20 is shown. The description starts with the IF signal $r_{IF}(t)$ at the IF frequency, e.g. $f_{IF} = 21.4$ MHz. For simplification the IF signal is not yet bandlimited. The bandwidth W_A of signal section 20 of 8 MHz is modelled by the subsequent IF filter 21 with the frequency transfer function $H_{IF}(f)$. The schematic spectrum $R_{IF}(f)$ of the input signal is shown in fig. 3. The bandwidth BW_{OFDM} of the spectrum of the OFDM signal and the reduced bandwidth BW_A of the analysing device 40 are indicated in fig. 3. It can be seen that the middle of the OFDM spectrum (at sub-carrier $k=0$) is shifted from the IF frequency f_{IF} by the

user definable frequency offset f_{offset} . By varying f_{offset} the position of the analysing window 39 can be changed. If for example the frequency offset is set to $f_{\text{offset}}=0$, the analysing window 39 is set in the middle of the OFDM spectrum. Furthermore, the schematic transfer function $H_{IF}(f)$ is shown in fig. 3. The passband bandwidth BW_A of the example is 8 MHz and symmetric to the IF frequency. The sub-carriers in the undistorted passband will be analysed.

10

The main task of the IF filter 21 is to avoid aliasing effects in the 8 MHz analysing window by the subsequent sampling process of the Analog to Digital Converter (ADC) 22. The sampling rate of the ADC is e.g. $f_s = 32$ MHz.

15

Next, the sampled IF sequence is multiplied with the sequence $e^{-j\omega_{IF}T_n}$ in multiplier 26, whereby the sampling period is defined by $T_n = 1/f_s$. This complex multiplication effects a spectral shift from the IF frequency f_{IF} to base band.

20

The following low pass filter 24 with the transfer function $H_{LP}(f)$ also possesses the passband bandwidth of 8 MHz, see schematic plot in fig. 3, and fulfils two tasks:

25

- Suppression of the mirror at $f = -2f_{IF}$ caused by the spectral shift.
- The low pass filter 24 must avoid aliasing effects in the e.g. 8 MHz analysing window 39 caused by the subsequent resampling process. As the resampling process reduces the sample rate, the transition band at low pass filter 24 must be steeper compared to the IF filter 21.

30

35

Next the sampling must be changed to the Nyquist rate. This is performed by a digital resampler 25. The output

sequence is generated at the desired Nyquist rate of e.g. $f_n = 20$ MHz.

5 Afterwards the resampled sequence is multiplied with the sequence $e^{-j2\pi f_{off} n T_{n2}}$ in multiplier 26. This operation generates a further spectral shift by the frequency f_{off} . This spectral shift can be integrated in the first downconversion, if the resampling process does not require a low pass input sequence. The resulting output sequence
10 is $r(i)$.

The schematic spectrum $R(f)$ again is shown in fig. 3. It is transparent that $r(i)$ is the OFDM signal in baseband position, i.e. the channel $k=0$ is located at the
15 frequency $f=0$. Furthermore, the sub-carriers within the analysing window 39 of 8 MHz are not distorted. The position of the analysing window can be chosen by the correspondent frequency offset f_{offset} .

20 Afterwards, the sequence $r(i)$ enters into the W-LAN application 7 which is identical to the wideband FSQ implementation shown in fig. 1. Thus reference is made to the lower part of fig. 1.

25 According to one aspect of the present invention it is important that the length τ of the impulse response $h(t)$ the low pass filter 24 is shorter than the length T_{GA} of the guard periods of the data symbols. To illustrate this, two data symbols S1 and S2 of the data sequence of one of
30 the pilot carriers is shown in fig. 4. It can be seen that the useful part 30 of each data symbol is separated from a neighbouring data symbol by a guard period 31, which has the time length T_{GP} . The lower part of fig. 4 illustrates the time shift resulting from the low pass filter 24.

35 The impulse response $h(t)$ of low pass filter 24 has a specific length τ . There are several possibilities to define the length τ of the impulse response $h(t)$. One possibility is illustrated in fig. 5. Fig. 5 shows a

typical impulse response $h(t)$ of a low pass filter. The filter is treated with a dirac impulse at time $t=0$. The impulse response $h(t)$ decreases from starting value A to value $1/e \cdot A$ within the time period τ which can be used as a definition of the length τ of the impulse response $h(t)$.

This length τ can also be defined from the bandwidth BW_A of the filter. If low pass filter 24 has a bandwidth BW_A of 8 MHz the length τ of the impulse response of the filter 24 can be defined as

$$\tau = 1/BW_A.$$

In the embodiment discussed above it is

$$\tau = 1/8\text{MHz} = 125\text{ns}$$

This definition is used within this application, i.e. the length τ of the impulse response of low pass filter 24 is defined as the inverse $1/BW_A$ of the bandwidth BW_A of the low pass filter 24.

The length τ of the impulse response $h(t)$ is preferably shorter than $1/4$ of the length T_{GP} of guard periods 31 and most preferably about $2.5/16$ of the length T_{GP} of the guard periods 31, as in the example of IEEE W-LAN standard the length T_{GP} of the guard periods 31 has the length of 16 symbols, which is $16 \cdot 50 \text{ ns} = 800 \text{ ns}$, and 125 ns length of impulse response is equivalent to the length of 2.5 symbols, thus $\tau/T_{GP} = 2.5/16$.

Thus, only small inter symbol interference (ISI) have to be expected. Simulations have confirmed this statement.

Further it is important to note, how many sub-carriers can be analysed in a measurement. The maximum number of sub-carriers within the transmission band of 8 MHz is

$$nof_{Subcarrier} = \frac{f_{pass}}{f_{bin}} = \frac{8 \text{ MHz}}{312.5 \text{ kHz}} \approx 25 .$$

From a more conservative view about 20 sub-carriers can be used for the measurement.

5

It should be noticed that even this bandlimited measurement supports symbolwise tracking. This is possible because there are according to the invention always 2 pilot sub-carriers of the total 4 pilot sub-carriers within the 8 MHz analysing window. The pilots are used for symbolwise tracking, i.e. optional phase and/or timing and/or gain. The smaller number of used pilot carriers (2 instead of usually 4) leads to a higher estimation error of the synchronisation parameters $\hat{\Delta f}_l, \hat{\xi}_l$ and consequently to an increase of the EVM compared to a measurement with no limitation of the bandwidth. The statistical increase can be calculated however and can be compensated by averaging the synchronisation parameters $\hat{\Delta f}_l, \hat{\xi}_l$ over several data symbols.


20

Furthermore, simulations have shown that the preamble synchronisation also works well in the case of the bandlimited OFDM signal and is robust for low signal to noise ratios.

25

Fig. 6 shows a typical screen plot of an analysing device 40. Section 41 shows the bursts of a specific sub-carrier of the OFDM signal. Section 42 shows the constellation diagram on a specific sub-carrier. Section 43 indicates *EVM* of all carriers, of the data carriers, the pilot carriers and the free carriers. Further, the IQ-Offset, IQ-Imbalance and quadrature mismatch are shown. Section 44 shows a diagram with *EVM* as a function of the sub-carrier number.

35



P27512/EP/P1

Claims

5 1. Method for analysing an OFDM signal ($r_{IF}(t)$) with an
analysing device (40) having a signal section (20) with a
bandwidth (BW_A) smaller than the bandwidth (BW_{OFDM}) of
the OFDM signal, the OFDM signal ($r_{IF}(t)$) transporting a
series of data symbols ($S1, S2, \dots$) on several orthogonal
10 carrier frequencies, each data symbol ($S1$) having a useful
part (30) separated by a guard period (31) from
neighbouring data symbols ($S2$),
comprising the steps of low pass filtering of the OFDM
signal with a low pass filter (24) and shifting (26) the
15 spectrum of the OFDM signal in order to obtain a frequency
shifted filtered OFDM signal ($r(i)$),
whereby the length (τ) of the impulse response ($h(t)$) of
the low pass filter (24) is shorter than the length (T_{GP})
of the guard periods (31) of the data symbols ($S1, S2,$
20 \dots).

2. Method according to claim 1,
characterised in that
the length (τ) of the impulse response ($h(t)$) of the low
25 pass filter (24) is shorter than $\frac{1}{4}$ of the length (T_{GP}) of
the guard periods (31) of the data symbols ($S1, S2, \dots$).

3. Method according to claim 2,
characterised in that
30 the length (τ) of the impulse response ($h(t)$) of the low
pass filter (24) is about $2.5/16$ of the length (T_{GP}) of
guard periods (31) of the data symbols ($S1, S2, \dots$).

4. Method for analysing an OFDM signal ($r_{IF}(t)$) transporting
35 a series of data symbols ($S1, S2, \dots$) on several
orthogonal carrier frequencies with an analysing device
(40) having a signal section (20) with a bandwidth (BW_A)
smaller than the bandwidth (BW_{OFDM}) of the OFDM signal,

whereby a first specific number of carrier frequencies transport a pilot signal within the OFDM signal, comprising the steps of low pass filtering of the OFDM signal with a low pass filter (24) and shifting (26) the spectrum of the OFDM signal in order to obtain a frequency shifted filtered OFDM signal ($r(i)$), and estimating (12) several synchronisation parameters ($\hat{\Delta f}_l, \hat{\xi}_l$) of the OFDM signal by use of the pilot signal, whereby the number of useful carrier frequencies transporting the pilot signal is reduced to a second specific number by the signal section (20) with its bandwidth (BW_A) smaller than the bandwidth (BW_{OFDM}) of the OFDM signal and averaging (12) the estimated synchronisation parameters ($\hat{\Delta f}_l, \hat{\xi}_l$) of the OFDM signal over several data symbols in order to compensate the reduced number of useful carrier frequencies transporting the pilot signal.

5. Method according to claim 4,
 20 **characterised in that**
 the first specific number is 4 and the second specific number is 2.

6. Method according to claim 4 or 5,
 25 **characterised in that**
 the estimated characteristic values of the OFDM signal are symbolwise frequency offset ($\hat{\Delta f}_l$) and/or clock offset ($\hat{\xi}_l$) and/or phase offset resulting therefrom and/or gain (\hat{g}_l).

7. Method according to any of claims 4 to 6,
 30 **characterised in that**
 each data symbol (S1) has a useful part (30) separated by a guard period (31) from neighbouring data symbols (S2), whereby the length (τ) of the impulse response ($h(t)$) of the low pass filter (24) is shorter than the length (T_{GP}) of the guard periods (31) of the data symbols (S1, S2, ...).

8. Method according to claim 7,

characterised in that

the length (τ) of the impulse response ($h(t)$) of the low pass filter (24) is shorter than $\frac{1}{4}$ of the length of the guard periods (31) of the data symbols (S_1, S_2, \dots).

5

9. Method according to any of claims 4 to 8,

characterised in that

the estimation of the synchronisation parameters is done for each symbol of the pilot signal and is averaged over several symbols.

10

10. Method according to claim 9,

characterised in that

the length (τ) of the impulse response ($h(t)$) of the low pass filter (24) is about $2.5/16$ of the length of the guard periods (31) of the data symbols (S_1, S_2, \dots).

15

11. Method according to any of claims 1 to 10,

characterised in that

the OFDM signal is resampled (25) after low pass filtering (24).

20

12. Analysing device (40) for analysing an OFDM signal ($r_{IF}(t)$) transporting a series of data symbols (S_1, S_2, \dots)

25

on several orthogonal carrier frequencies, each data symbol (S_1) having a useful part (30) separated by a guard period (31) from neighbouring data symbols (S_2),

whereby the analysing device (40) has a signal section (20) with a bandwidth (BW_A) smaller than the bandwidth (BW_{OFDM}) of the OFDM signal,

30

whereby the analysing device (40) has a low pass filter (24) for low pass filtering of the OFDM signal and a frequency shifter (26) for shifting the spectrum of the OFDM signal in order to obtain a frequency shifted filtered OFDM signal ($r(i)$), and

35

whereby the length (τ) of the impulse response ($h(t)$) of the low pass filter (24) is shorter than the length (T_{GP}) of the guard periods (31) of the data symbols (S_1, S_2, \dots).

13. Analysing device (40) for analysing an OFDM signal ($r_{IF}(t)$) transporting a series of data symbols (S_1, S_2, \dots) on several orthogonal carrier frequencies,

5 whereby the analysing device (40) has a signal section (20) with a bandwidth (BW_A) smaller than the bandwidth (BW_{OFDM}) of the OFDM signal within the OFDM signal, whereby a first specific number of carrier frequencies transport a pilot signal,

10 whereby the analysing device (40) has a low pass filter (24) for low pass filtering of the OFDM signal and a frequency shifter (26) for shifting the spectrum of the OFDM signal in order to obtain a frequency shifted filtered OFDM signal ($r(i)$), and estimating means (12) for

15 estimating several synchronisation parameters ($\hat{\Delta f}_l, \hat{\xi}_l$) of the OFDM signal by use of the pilot signal, whereby the number of carrier frequencies transporting the pilot signal is reduced to a second specific number by the signal section (20) with its bandwidth (BW_A) smaller than

20 the bandwidth (BW_{OFDM}) of the OFDM signal and whereby the estimating means (12) averages the estimated synchronisation parameters ($\hat{\Delta f}_l, \hat{\xi}_l$) of the OFDM signal over several data symbols l in order to compensate the reduced number of carrier frequencies transporting the pilot

25 signal.

14. Digital storage medium with control signals electronically readable from the digital storage medium, which interact with a programmable computer or digital

30 signal processor in a manner that all steps of the method according to any of claims 1 to 11 can be performed.

15. Computer-program-product with program-code-means stored on a machinereadable data carrier to perform all

35 steps of any of claims 1 to 11, when the program is performed on a programmable computer or a digital signal processor.

16. Computer program with programm-code-means to perform all steps of any of claims 1 to 11, when the program is performed on a programmable computer or a digital signal processor.

5

17. Computer program with program-code-means to perform all steps of any of claims 1 to 11, when the program is stored on a machinereadable data carrier.

1
The first part of the report deals with the general situation of the country and the progress of the work during the year. It is followed by a detailed account of the various projects and the results achieved. The report concludes with a summary of the work done and the plans for the future.

The second part of the report deals with the financial aspects of the work. It gives a detailed account of the income and expenditure for the year, and shows how the funds have been used. It also includes a statement of the assets and liabilities of the organization at the end of the year.

P27512/EP/P1

Abstract

5 The invention concerns a method for analysing an OFDM
signal ($r_{IF}(t)$) transporting a series of data symbols on
several orthogonal carrier frequencies, each data symbol
having a useful part separated by a guard period from
neighbouring data symbols, with an analysing device (40)
10 having a signal section (20) with a bandwidth (BW_A)
smaller than the bandwidth (BW_{OFDM}) of the OFDM signal.
The method comprises the steps of low pass filtering of
the OFDM signal with a low pass filter (24) and shifting
(26) the spectrum of the OFDM signal in order to obtain a
15 frequency shifted filtered OFDM signal ($r(i)$), whereby the
length of the impulse response of the low pass filter (24)
is shorter than the length of the guard periods of the
data symbols.

20

(fig. 2 and fig. 3)

40




Fig. 1




Fig. 2




Fig. 3



The diagram shows two horizontal bars representing stages S1 and S2. Each bar is divided into a 'guard' section (width 31) and a 'useful part' (width 30). The top bar (S1) starts at time 0. The bottom bar (S2) starts at time T6P. The time axis t is indicated at the bottom right.

P27512

THIS PAGE BLANK (USPTO)